



Omskifter for Netsp

H 220~	H 127~
R	R
S	S
H 110=	H 150=
R	R R17
S	S

Type SU110

MF 447 kHz.

Alle Maalinger foretaget ved 220V~
Instrument 1000 Ohm pr. Volt.

C. 1	5000 pF	2000 V. ω	<i>Super Electric</i>
C. 2	100 pF	keramisk	<i>Hescho</i>
C. 3	150 pF	keramisk	<i>Hescho</i>
C. 4	500 pF	Drejekondensator	<i>Torotor</i>
C. 5	0,1 MF	2000 V. ω	<i>Janko</i>
C. 6	200 pF	keramisk	<i>Hescho</i>
C. 7	20000 pF	2000 V. ω	<i>Super Electric</i>
C. 8	10 pF	keramisk	<i>Hescho</i>
C. 9	50000 pF	2000 V. ω	<i>Super Electric</i>
C. 10	20000 pF	2000 V. ω	<i>Super Electric</i>
C. 11	200 MF	12 V. Elektrolyt	<i>Janko</i>
C. 12	0,1 MF	2000 V. ω	<i>Siemens</i>
C. 13	24 MF	350 V. Elektrolyt	<i>Super Electric</i>
C. 14	0,25 MF	500 V. ω	<i>Wicon</i>
C. 15	0,5 MF	500 V. ω	<i>Wicon</i>
C. 16	250 pF	500 V. ω	<i>Super Electric</i>
C. 17	328 pF	keramisk	<i>Hescho</i>
C. 18	435 pF	keramisk	<i>Hescho</i>
C. 19	40 pF	Trimmer	<i>M. E. C.</i>
C. 20	90 pF	Trimmer	<i>M. E. C.</i>
C. 21	10000 pF	2000 V. ω	<i>Super Electric</i>
C. 22	16 MF	350 V. Elektrolyt	<i>Super Electric</i>
C. 23	1000 pF	1500 V. ω	<i>Super Electric</i>
Tr.	Udgangstransformator		<i>Peerless</i>
	UY 1 N - UCH 21 - UCH 21 - UBL 21		<i>Philips</i>
	Skalalampe 60 V, 0,1 Amp.		<i>S. M.</i>
	Omskifter for Netspænding		<i>Arako</i>
	Autotransformator		<i>Reolon</i>
	Lampesokler, Antennedaase, Grammofondaase		<i>T. I. K.</i>
	Højttaler		<i>Peerless</i>

R. 1	1 Meg. Ohm	0,5 Watt	<i>Erie</i>
R. 2	10000 Ohm	1 Watt	<i>Erie</i>
R. 3	30000 Ohm	1 Watt	<i>Erie</i>
R. 4	50000 Ohm	0,5 Watt	<i>Erie</i>
R. 5	0,2 Meg. Ohm	0,5 Watt	<i>Erie</i>
R. 6	0,1 Meg. Ohm	0,5 Watt	<i>Erie</i>
R. 7	0,5 Meg. Ohm	Potentiometer	<i>Vitrohm</i>
R. 8	640 Ohm	0,5 Watt	<i>Vitrohm</i>
R. 9	25 Ohm	1 Watt	<i>Vitrohm</i>
R. 10	100 Ohm	1 Watt	<i>Vitrohm</i>
R. 11	24 Ohm	0,5 Watt	<i>Erie</i>
R. 12	51 Ohm	0,5 Watt	<i>Erie</i>
R. 13	160 Ohm	0,5 Watt	<i>Erie</i>
R. 14	100 Ohm	3 Watt	<i>Vitrohm</i>
R. 15	1000 Ohm	0,5 Watt	<i>Erie</i>
R. 16	145 Ohm	3 Watt	<i>Erie</i>
R. 17	200 Ohm	10 Watt	
R. 18	1000 Ohm	1 Watt	<i>Erie</i>
L. 1		Sugekreds	<i>Arako</i>
L. 2		H. F. Filter	<i>Arako</i>
L. 3-4		M. F. Spoler	<i>Arako</i>
O. 1-2-3		Omskifttere	<i>M. E. C.</i>
O. 4		Tonekontrol	<i>M. E. C.</i>
O. 5		Netafbryder paabygget Potentiometer	
Dr.	300 Ohm	Filterspole	<i>Reolon</i>
Si.	0,3 Amp.	Sikring	