



KABLER TIL KONSOL (INTERNT)

		<u>V.no.</u>	<u>Tegnings no.</u>
1)	2 pol minifit - højttaler	56.119	3-0-35454A
2)	Kabel medfølger terminalen (power)	xx.xxx	x-x-xxxxx
3)	4 pol minifit - switch	56.120	3-0-35456B
4)	Kabel medfølger printeren (rundt stik - nc) (power)	xx.xxx	x-x-xxxxx
5)	Kabel medfølger Sat -C (Sub D 15 pol hun - nc) (power)	xx.xxx	x-x-xxxxx
6)	Sub D 15 pol han - hun (I/O interface)	56.124	3-0-35165A
7)	TNC - N CONN. (RG223) med vinkel beslag.	56.116	3-3-33921A
8)	Kabel medfølger VHF (firkantet stik - nc) (power)	xx.xxx	x-x-xxxxx
9)	Sub D 15 pol han HD - nc (option)	56.114	3-3-30467C
10)	Sub D 15 pol han HD - nc (sparc)	56.114	3-3-30467C
16)	Standard kabel (sub D 9 pol han - hun) (Bat 1)	56.123	3-0-35167A
17)	Standard kabel (sub D 9 pol han - hun) (Bat 2)	56.123	3-0-35167A
23)	Kabel medfølger printeren (rundt stik - nc) (power)	xx.xxx	x-x-xxxxx
24)	Kabel medfølger terminalen. (power)	xx.xxx	x-x-xxxxx
25)	TNC - N CONN. (RG223) med vinkel beslag.	56.116	3-3-33921A
26)	Kabel medfølger Sat -C (Sub D 15 pol hun - nc) (power)	xx.xxx	x-x-xxxxx
27)	Sub D 15 pol han - hun (I/O interface)	56.124	3-0-35165A
30)	2 pol mini fit - 2 stk halogen fatning.	56.118	3-0-35609B
31)	Standard kabel (sub D 9 pol han - hun) (scanbus)	56.123	3-0-35167A
32)	Standard kabel (sub D 9 pol han - hun) (L.S. / sparc bus)	56.123	3-0-35167A
33)	2 pol MT fatning - switch (on / off kabel til Sat C)	56.121	3-0-35455A
34)	2 pol MT fatning - switch (on / off kabel til Sat C)	56.121	3-0-35455A
36)	Standard kabel (sub D 9 pol han - hun) <u>KUN VED RADIOTELEX</u>	56.123	3-0-35167A
37)	8 pol mini din - switch (paper alarm)	56.122	3-0-35511A
38)	8 pol mini din - switch (paper alarm)	56.122	3-0-35511A

ENS KABLER

2, 24
4, 23
5, 26
6, 27
7, 25
9, 10
16, 17, 31, 32, 36
33, 34
37, 38

Forbindelse mellem: Connectionboard & PCH4652

Connectors: nc - nc

Forbindelser: Connectionboard X20 - PCH4652 X3

X20	PCH4652 X3
1	2
2	1
3	3
4	4
5	8
6	
7	7
8	

Forbindelse mellem: HT4520 MF/HF Trans.(Telex) - Connectionboard (X17)

Connectors: nc - nc

Forbindelser:

HT4520 (Com)	X17
1	1
2	2
3	3
4	4

Twisted Pairs (X17):

1	2
3	4

Forbindelse mellem: Transceiver (ac alarm) - Connectionboard (X31)

Connectors: nc - nc

Forbindelser:

X31	Remote
1	5
2	6

Forbindelse mellem: Connectionboard & VHF (Option + Sparc)

Connectors: Sub D 15 Pol HD Han - NC

V.no: 56.114 (3-3-30467C)

Forbindelser (Option):

Signal	Sub D 15 pol HD	X34
NMEA+	4 (Blå / Hvid)	1
NMEA-	5 (blå)	2

Twisted Pairs (Option) (X34):

1	2
---	---

Forbindelser (Sparc):

Signal	Sub D 15 pol HD	X27
+12V	7 (Orange / Hvid)	1
+12V	10 (Sort / hvid)	1
GND	6 (Orange + Rød)	2
SPARC+	2 (Gul)	3
SPARC-	3 (Gul / Sort)	4

Twisted Pairs (Sparc) (X27):

1	2
3	4

Forbindelse mellem: Transceiver (Scanbus) & Connectionboard (X23)

Connectors: nc - nc

Forbindelser:

Trans.	(X23)
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9

Twisted Pairs:

0	1
2	3
4	5
6	7
8	9

Forbindelse mellem: Alarmpanel (power) - Connectionboard (X5)

Connectors: Sub D 9 pol hun - nc

Forbindelser:

Sub D 9 pol Hun	X5
7	1
6	2
9	3
8	4

Twisted Pairs (X5):

1	2
3	4

Forbindelse mellem: Alarmpanel (VHF) - Connectionboard (X18)

Connectors: Sub D 9 pol han - nc

Forbindelser:

Sub D 9 pol Han	X18
9	1
2	2
3	3
5	4

Twisted Pairs (X18):

1	2
3	4

Forbindelse mellem: Alarmpanel (MF/HF) - Connectionboard (X10)

Connectors: Sub D 9 pol han - nc

Forbindelser:

Sub D 9 pol Han	X10
9	1
2	2
3	3
5	4

Twisted Pairs (X10):

1	2
3	4

Forbindelse mellem: Alarmpanel (Sat C) - Connectionboard (X28 / X42)

Connectors: Sub D 9 pol han - nc

Forbindelser:

Sub D 9 pol Han	X28 / X42
2	2
3	3
4	4
6	6
7	7
9	9

Twisted Pairs (X28 / 42):

3	6
4	0
2	9
7	0