



SIGNATUR- OG DELEFORTEGNELSE

Part nr.	Part nr.	Part nr.	Part nr.
C 1 Keram. 10pF-10 % 550	C 61 Olie 1nF-350 = 541	R 66 Kulmodst. 1,1 K ohm-½ watt.. 615	L 15 LB antennespole 2585
C 2 » 1,5nF-20-50 % 550	C 62 » 3nF-350 = 541	R 68 » 47 K ohm-½ watt.. 615	L 16 KB oscillatorspole 2586
C 3 » 560pF-10 % 550	C 63 » 10nF-350 = 541	R 69 » 22 K ohm-½ watt.. 615	L 17 FB » 5287
C 4 » 100pF-20 % 550	C 64 » 10nF-350 = 541	R 70 » 1 M ohm-½ watt.. 615	L 18 MB » 2588
C 6 » 6pF-20 % 550	C 66 Keram. 330pF-20 % 550	R 71 » 220 K ohm-½ watt.. 615	L 19 LB » 2589
C 7 Trimmer 30pF-variabel 4279	C 67 » 10nF-20-50 % 550	R 72 » 10 M ohm-½ watt.. 615	L 41 Rejektorfilter 7201
C 8 Keram. 100pF-20 % 550	C 69 Elko 4μF-50/60 V. 500	R 73 » 220 K ohm-½ watt.. 615	L 50 MF transformer 10,9 2603
C 9 » 50pF-10 % 550	C 71 » 32μF-320/350 V. 502	R 74 » 220 K ohm-½ watt.. 615	L 51 MF » 449 2606
C 10 » 15pF-10 % 550	C 72 Olie 20nF-600 = 542	R 75 Potm. 1 M ohm kurve 831..... 688	L 52 Forholds detektorkreds 2625
C 11 » 20pF-10 % 550	C 74 » 5nF-5000 = 543	R 77 Kulmodst. 100 K ohm-½ watt 615	L 53 MF transformer 449 2607
C 12 » 15pF-10 % 550	C 76 » 50nF-600 = 542	R 82 » 680 K ohm-½ watt 615	L 93 Netfilter 7202
C 13 » 572pF- 5 % 550	C 82 » 10nF-600 = 542	R 83 » 1,1 K ohm-½ watt 615	L 94 Drosselspole 10 Mikro Hy ... 2608
C 16 » 33pF-10 % 550	C 83 Elko 2×32μF-320/350 V. 496	R 85 » 1,1 K ohm-½ watt 615	L 95 Udgangstrafo 5010
C 17 » 1,5nF-20-50 % 550	C 84 Olie 50nF-600 = 542	R 86 » 10 K ohm-½ watt 615	Toneomstiller 746
C 18 » 1,5nF-20-50 % 550	C 85 Elko 25μF-25/50 V. 448	R 89 » 75 ohm-½ watt 615	Områdeomstiller 745
C 20 » 68pF- 5 % 550	C 87 Olie 20nF-350 = 541	R 91 Tråd GL 2000 ohm-3 watt ... 5115	Dobb. trimmer 4286
C 21 » 68pF- 5 % 550	C 90 Keram. 4,7nF-20-50 % 550	R 92 » GL 400 ohm-3 watt ... 5115	Drejekondensator 6205
C 22 » 150pF- 5 % 550	R 1 Kulmodst. 100 ohm-½-watt.. 615	R 93 » EK 375 ohm-5 watt ... 5110	Snorskive til do. 2865
C 23 » 445pF- 5 % 550	R 2 » 1,1 K ohm-½ watt... 615	R 94 » GLT 50 ohm 5114	Ensretterventil 6303
C 24 Trolitul 1330pF-10 % 550	R 3 » 33 K ohm-½ watt... 615	R 96 » GL 150 ohm-3 watt 5115	Skalalamper 18V/0,1 A 642 A
C 26 Keram. 470pF-20 % 550	R 4 » 10 K ohm-½ watt... 615	R 97 NTC (Ph. 100.026/01) 648	Højttaler 7307-10 K.
C 27 » 47pF-20 % 550	R 41 » 15 K ohm-½ watt... 615	R 98 NTC (Ph. 100.092) 650	Kabinet, blank nød 5238B/N
C 41 » 572pF- 5 % 550	R 46 » 22 K ohm-½ watt... 615	R 99 NTC (Ph. 100.092) 650	Kabinet, mat nød 5238M/N
C 43 » 22pF-10 % 550	R 47 » 2 M ohm-½ watt... 615	R 101 Kulmodst. 22 K ohm-½ watt.. 615	Kabinet, teak 5238 T
C 45 Olie 1nF-5000 = 543	R 48 » 75 ohm-½ watt... 615	R 102 » 22 K ohm-½ watt.. 615	Øjeindfatning 6802
C 46 Keram. 10nF-20-50 % 550	R 49 » 47 K ohm-½ watt... 615	R 103 » 1,1 K ohm-½ watt.. 615	Bagklædning 7705
C 47 » 10nF-20-50 % 550	R 51 » 22 K ohm-½ watt... 615	R 104 » 2 M ohm-½ watt.. 615	Bundplade 2347
C 48 » 10nF-20-50 % 550	R 52 » 2 M ohm-½ watt... 615	R 105 » 100 K ohm-½ watt.. 615	Skala 2291
C 49 Olie 5nF-5000 = 543	R 53 » 1,1 K ohm-½ watt... 615	L 1 Antennespole 2590	Viser 2965
C 51 Keram. 4,7nF-20-50 % 550	R 54 » 47 K ohm-½ watt... 615	L 2 Drosselspole 2591	Skalalampholder 3207
C 53 Olie 5nF-350 = 541	R 55 » 2 M ohm-½ watt... 615	L 3 HF anodespole 2592	Skalabaggrund 6798
C 54 » 10nF-350 = 541	R 56 » 2 M ohm-½ watt... 615	L 4 Oscillatorspole 2593	Sikring 0,5 A m/ trådender 651
C 55 Keram. 10nF-20-50 % 550	R 57 » 1 M ohm-½ watt... 615	L 5 MF primær spole 2594	Stof 2050
C 56 » 100pF-20 % 550	R 58 » 1 M ohm-½ watt... 615	L 6 MF sekundær spole 2595	Knapper 7526
C 58 » 100pF-20 % 550	R 62 » 510 ohm-½ watt... 615	L 12 KB antennespole 2582	Plasticprofil 6510 B
C 59 » 10nF-20-50 % 550	R 64 » 75 ohm-½ watt... 615	L 13 FB » 2583	Emballage 4211
		L 14 MB » 2584	

Ved bestilling af reservedele bedes partnummer og modtagerens fabrikationsnummer angivet.