



SIGNATUR- OG DELEFORTEGNELSE

Part nr.	Part nr.	Part nr.	Part nr.
C 1 Keram. 10pF-10 % 550	C 66 Keram. 330pF-20 % 550	R 67 Kulmodst. 220 K ohm-½ watt 615	L 17 FB oscillatorspole 2587
C 2 » 1,5N-20/50 % 550	C 67 Olie Papir 20N-350 = 541	R 68 » 47 K ohm-½-watt... 615	L 18 MB » 2588
C 3 » 560pF-10 % 550	C 68 Keram. 180pF-10 % 550	R 69 » 22 K ohm-½-watt... 615	L 19 LB » 2589
C 4 » 100pF-20 % 550	C 69 Elko 4μF-50/60 = 500	R 70 » 1 M ohm-½-watt... 615	L 30 MB ferritspole 2596
C 6 » 6pF-20 % 550	C 71 » 32μF-320/350 = 502	R 71 » 220 K ohm-½-watt... 615	L 30 MB » 2596
C 7 Trimmer 30pF-variabel 4279	C 72 Olie Papir 20N-600 = 542	R 72 » 10 M ohm-½ watt... 615	L 31 LB » 2597
C 8 Keram. 100pF-20 % 550	C 74 » » 5N-5000 = 543	R 73 » 220 K ohm-½ watt... 615	L 31 LB » 2597
C 9 » 50pF-10 % 550	C 76 » » 50N-600 = 542	R 74 » 39 K ohm-½ watt... 615	L 41 Rejektorspole 2508
C 10 » 15pF-10 % 550	C 77 » » 0,1μF-350 = 541	R 75 Potm. 1 M ohm (Udtag 200K)	L 50 MF transformer 10,9 2603
C 11 » 20pF-10 % 550	C 78 » » 50N-350 = 541	70 m/m 688	L 51 MF » 449 2606
C 12 » 15pF-10 % 550	C 79 Elko 25μF-25/30= 488	R 76 Kulmodst. 82 K ohm-½ watt... 615	L 52 Forholds detektorkreds 2604
C 13 » 572pF- 5 % 550	C 81 Olie Papir 0,1μF-600 = 542	R 77 » 100 K ohm-½ watt... 615	L 53 MF transformer 449 2621
C 16 » 33pF-10 % 550	C 82 » » 5N-600 = 542	R 78 » 350 ohm-½ watt... 615	L 57 9 Khz filter 2605
C 17 » 1,5N-20/50 % 550	C 83 Elko 32+32μF-320/350 = 496	R 79 » 2,7 K ohm-½ watt... 615	L 93 Netfilter 7202
C 18 » 1,5N-20/50 % 550	C 84 Olie Papir 50N-600 = 542	R 81 » 100 ohm-½ watt... 615	L 94 Drosselspole 10 Mikro Hy 2608
C 20 » 68pF- 5 % 550	C 86 » » 50N-600 = 542	R 82 » 680 K ohm-½ watt... 615	Tonedrosselspole 5018
C 21 » 68pF- 5 % 550	C 91 Keram. 10N-20/50 % 550	R 83 » 1 K ohm-½ watt... 615	Udgangstransformer 5017
C 22 » 150pF- 5 % 550	R 1 Kulmodst. 100 ohm-½ watt ... 615	R 84 » 150 ohm-1 watt... 616	Toneomstiller 741
C 23 » 445pF- 5 % 550	R 2 » 1 K ohm-½ watt... 615	R 86 » 1 K ohm-½ watt... 615	Områdeomstiller 744
C 24 Trolitul 1350pF-5 % 550	R 3 » 33 K ohm-½ watt... 615	R 88 » 1 K ohm-½ watt... 615	Dobb. trimmer 4287
C 26 Keram. 470pF-20 % 550	R 4 » 10 K ohm-½ watt... 615	R 89 » 75 ohm-½ watt... 615	Drejekondensator 6205
C 27 » 47pF-20 % 550	R 41 » 15 K ohm-½ watt... 615	R 90 Potm. 20 ohm-Tråd 695	Snorskive til do 2865
C 41 » 572pF- 5 % 550	R 46 » 22 K ohm-½ watt... 615	R 91 Tråd GL 2000 ohm-3 watt..... 5115	Snorskive Ferrit 2863
C 45 Olie Papir 1N-5000 = 543	R 47 » 2 M ohm-½ watt... 615	R 92 » GL 400 ohm-3-watt..... 5115	Ferritstave 334
C 46 Keram. 10N-20/50 % 550	R 48 » 75 ohm-½ watt... 615	R 93 Kulmodst. 150 ohm-1 watt..... 616	Ensretterventil 6303
C 47 » 10N-20/50 % 550	R 49 » 47 K ohm-½ watt... 615	R 94 Tråd GLT 50 ohm-3 watt..... 5114	Skalalamer 18/0,1 642 A
C 48 » 10N-20/50 % 550	R 50 » 33 K ohm-½ watt... 615	R 96 Kulmodst. 3,9 M ohm-½ watt 615	Højttaler 774
C 49 Olie Papir 5N-5000 = 543	R 51 » 22 K ohm-½ watt... 615	R 97 » 2 M ohm-½ watt 615	Kabinet 5222
C 50 Keram. 22pF-10 % 550	R 52 » 2 M ohm-½ watt... 615	R 101 Tråd EL 1120 ohm-15 watt 5106	Bagklaædning 2344
C 51 » 4,7N-20/50 % 550	R 53 » 1 K ohm-½ watt... 615	R 102 Kulmodst. 100 K ohm-½ watt 615	Bundplade 2345
C 52 Olie Papir 1N-350 = 541	R 54 » 47 K ohm-½ watt... 615	R 103 » 2 M ohm-½ watt 615	Skala 2281
C 53 » » 10N-350 = 541	R 55 NTC (Ph. 100.026/01) 648	L 1 Antennespole 2590	Viser 2964
C 54 » » 20N-350 = 541	R 56 Kulmodst. 10 M ohm-½ watt... 615	L 2 Drosselspole 2591	Område-Indikatorskive 6747
C 55 Keram. 10N-20/50 % 550	R 57 » 47 K ohm-½ watt... 615	L 3 HF anodespole 2592	Tone- » 6748
C 56 » 100pF-20 % 550	R 58 » 470 K ohm-½ watt... 615	L 4 Oscillatorspole 2593	Dobb. viser 2963
C 57 » 4,7N-20/50 % 550	R 59 » 1 M ohm-½ watt... 615	L 5 MF primær spole 2594	Indicatorindfatning 6752
C 58 » 100pF-20 % 550	R 60 Tråd GL 360 ohm-3 5115	L 6 MF sekundær spole 2595	Sikring 0,5 A u/tråd 652
C 59 » 10N-20/50 % 550	R 61 Kulmodst. 1 M ohm-½ watt... 615	L 12 KB antennespole 2582	Stof 2046
C 61 Olie Papir 4N-350 = 541	R 62 » 330 ohm-½ watt... 615	L 13 FB » 2583	Dekorationssnor 2047
C 62 » » 10N-350 = 541	R 63 » 47 K ohm-½ watt... 615	L 14 MB » 2584	Overknapper 7507
C 63 » » 10N-350 = 541	R 64 » 75 ohm-½ watt... 615	L 15 LB » 2585	Underknapper 7506
C 64 » » 10N-350 = 541	R 66 » 1 K ohm-½ watt... 615	L 16 KB oscillatorspole 2586	Emballage 4202

Ved bestilling af reservedele bedes partnummer og modtagerens fabrikationsnummer angivet.