

# SAILOR

Service Information No. 154  
Kundendienst-Mitteilung No.  
Service Information No.  
Información de servicio No.  
Servicemeddelelse No.

Series / Serie / Numéro de série / Serie / Serie

Date / Datum / Date / Fecha / Dato

For a transitional period substitute types for zeener diodes will be used in T122, T121, R103, R104, R105 and R106.

After that period (abt. 1/11 1973 to 1/4 1974) types from Motorola will be used again exclusively.

The table overleaf shows an outline for the period, and we recommend you to follow the table.

N.B. - IMPORTANT!

If you should happen to be in possession of zeener diodes of the make Dickson with the type marks: 2EZ68D5 - 2EZ13D5 - 2EZ7,5D5 and 2EZ5,1D5 then avoid using them when changing zeener diodes in connection with servicing.



Please file this information in the service-portfolio we have sent you.

Bitte archivieren Sie diese Mitteilung in der Kundendienstmappe, die wir Ihnen gesandt haben.

Nous vous prions de bien vouloir classer ce document dans le dossier bleu qui vous

a été envoyé à cet effet.

Sivanse archivar esta información en la cubierta de servicio que les hemos enviado a Ustedes.

De bedes venligst arkivere denne meddelelse i den tilsendte servicemappe.

1/5 S. P. RAC

Aalborg - Denmark

Type of series	Zeener diode used in	Component Designation	Minimum Specification	Substitute during the period 1/11 1973 - 1/4 1974	Future substitute from abt. 1/4 1974 and on
R105	12/24V DC Converter	D1102	13V $\pm$ 5% - 1W	1N5350 A Motorola 1N4743 A Motorola 1N3023 B Motorola 1N4743 A AEG	1N5350 B Motorola
T122	Stabilized Power Unit	D1002	7,5V $\pm$ 5% - 0,4W	BZX79C7V5 Philips	1N4737 A Motorola
T122	Bal. Mixer	D501	7,5V $\pm$ 5% - 0,4W	BZX79C7V5 Philips	1N4737 A Motorola
T121	Bal. Mixer	D101	7,5V $\pm$ 5% - 0,4W	BZX79C7V5 Philips	1N4737 A Motorola
T121/T122	Microphone Ampl. and Clipper	D410	5,1V $\pm$ 5% - 0,4W	BZX79C5V1 Philips	1N4733 A Motorola
T121/T122	Alarm Signal Generator	D903	7,5V $\pm$ 5% - 1,3W	NT77C7V5 Nortron	NT77C7V5 Nortron 1N4737 A Motorola
T121/T122	Alarm Signal Generator	D905	68V $\pm$ 5% - 1W	1N4760 Motorola	1N4760 A Motorola
T122	AC/24V Power Unit	D1201	68V $\pm$ 5% - 1W	1N4760 Motorola	1N4760 A Motorola